

SIMULATION RESULTS FOR THE VLBA CORRELATOR

by John Benson, Chuck Broadwell, and Ray Escoffier

Oct. 16, 1987

The attached figures give the results of two programs developed to simulate the performance of the VLBA correlator. These simulators, and early results, were described in VLBA Correlator memos 74, 76, and 84. Further results were deemed desirable at this time because none of the earlier results used quantization levels now planned for the system. This memo will present the results of simulations that were made using the currently planned details of the correlator.

In addition to using current correlator quantization levels, this memo presents the results of experiments not simulated in earlier runs. For example, one-bit sample simulations, absorption line simulations and a three station run to check closure performance were performed and the result of these experiments are presented here.

The two simulation programs will still be distinguished from each other as was done in correlator memo 84 by the terms "hardware simulator" and "software simulator". The software simulator was written by John Benson and runs on a Cray computer and the hardware simulator runs on hardware built using TMS 32020 digital signal processing system.

The table below gives results of the simulations presented in this memo. Experiments labeled as narrow line observation used cw signals (not narrow bandwidth gaussian signals) to generate input data.

EXPERIMENT 1:

| | |
|-------------------------|---------------------|
| observation | 3-station continuum |
| simulator | software |
| correlation coefficient | 0.5 |
| integration length | 32 Msamples |
| figures (none) | |

COMMENT ON EXPERIMENT 1:

The software simulator was used to run a closure phase test for a point source model that is offset from the phase center. Each of the three baselines was integrated for 32 Msamples. The initial station phase and phase rates are shown below;

| | |
|-------------------|-----------------------------------|
| P1 = 25.20 deg., | $\dot{P}1 = 23641.71 \text{ Hz.}$ |
| P2 = -41.20 deg., | $\dot{P}2 = 35121.99 \text{ Hz.}$ |
| P3 = -13.70 deg., | $\dot{P}3 = 17229.78 \text{ Hz.}$ |

The measured closure phase was, $PC = 0.02\text{deg.} \pm 0.09\text{deg.}$ averaged across the spectrum.

EXPERIMENT 2:

| | |
|-------------------------|-------------------------------------|
| observation | continuum |
| simulator | hardware |
| correlation coefficient | 0.5 |
| integration length | 957 Msamples |
| figure 2A | station 1 |
| figure 2B | station 2 |
| figure 2C | cross power |
| figure 2D | station 1 rms deviation |
| figure 2E | cross power real rms deviation |
| figure 2F | cross power imaginary rms deviation |

EXPERIMENT 3:

| | |
|-------------------------|---------------------------|
| observation | continuum |
| simulator | software |
| correlation coefficient | 0.5 |
| integration length | 128 Msamples |
| figure 3 | station 1 and cross power |

EXPERIMENT 4:

| | |
|-------------------------|--------------|
| observation | wide line |
| simulator | hardware |
| correlation coefficient | 0.95 |
| integration length | 200 Msamples |
| figure 4A | station 1 |
| figure 4B | station 2 |
| figure 4C | cross power |

EXPERIMENT 5:

| | |
|-------------------------|--------------|
| observation | narrow line |
| simulator | software |
| correlation coefficient | 0.5 |
| integration length | 128 Msamples |
| figure 5A | station 1 |
| figure 5B | cross power |

EXPERIMENT 6:

| | |
|-------------------------|--------------|
| observation | narrow line |
| simulator | hardware |
| correlation coefficient | 0.5 |
| integration length | 438 Msamples |
| figure 6A | station 1 |
| figure 6B | cross power |

EXPERIMENT 7:

| | |
|-------------------------|-------------|
| observation | narrow line |
| simulator | software |
| correlation coefficient | 0.95 |
| integration length | 32 Msamples |
| figure 7A | station 1 |
| figure 7B | cross power |

EXPERIMENT 8:

| | |
|-------------------------|--------------|
| observation | narrow line |
| simulator | hardware |
| correlation coefficient | 0.95 |
| integration length | 103 Msamples |
| figure 8A | station 1 |
| figure 8B | station 2 |
| figure 8C | cross power |

EXPERIMENT 9:

| | |
|-------------------------|-----------------|
| observation | absorption line |
| simulator | software |
| correlation coefficient | 0.5 |
| integration length | 128 Msamples |
| figure 9A | station 1 |
| figure 9B | cross power |

EXPERIMENT 10:

| | |
|-------------------------|-----------------|
| observation | absorption line |
| simulator | hardware |
| correlation coefficient | 0.7 |
| integration length | 238 Msamples |
| figure 10A | station 1 |
| figure 10B | station 2 |
| figure 10C | cross power |

EXPERIMENT 11:

| | |
|-------------------------|--------------------|
| observation | absorption line |
| simulator | hardware |
| correlation coefficient | 0.95 |
| integration length | 152 Msamples |
| figure 11A | station 1 |
| figure 11B | station 2 |
| figure 11C | cross power |
| figure 11D | high precision FFT |

COMMENTS ON ABSORPTION LINE EXPERIMENTS:

Two single station integrations were run in order to put the station spectrum results of experiments 9, 10, and 11 in perspective. The output of the hardware simulators station signal was Fourier transformed by a high precision commercial FFT package both before and after quantization. The reason for these integrations was to compare which part of the degradation of the station spectrum was due to the low precision FFT and which to the sampling process. The results of these two runs are given in figure 11D.

EXPERIMENT 12:

| | |
|-------------------------|-----------------------------|
| observation | continuum, one bit sampling |
| simulator | hardware |
| correlation coefficient | 0.5 |
| integration length | 200 Msamples |
| figure 12A | station 1 |
| figure 12B | station 2 |
| figure 12C | cross power |

EXPERIMENT 13:

| | |
|-------------------------|-------------------------------|
| observation | narrow line. one bit sampling |
| simulator | software |
| correlation coefficient | 0.5 |
| integration length | 128 Msamples |
| figure 13A | station 1 |
| figure 13B | cross power |

EXPERIMENT 14:

| | |
|-------------------------|-------------------------------|
| observation | narrow line, one bit sampling |
| simulator | hardware |
| correlation coefficient | 0.5 |
| integration length | 127 Msamples |
| figure 14A | station 1 |
| figure 14B | station 2 |
| figure 14C | cross power |

EXPERIMENT 15:

| | |
|-------------------------|---------------------------------------|
| observation | narrow line, low relative fringe rate |
| simulator | hardware |
| correlation coefficient | 0.5 |
| fringe rate, antenna 1 | 1007.85 Hz |
| fringe rate, antenna 2 | 1000.00 Hz |
| integration length | 95 Msamples |
| figure 15A | station 1 |
| figure 15B | station 2 |
| figure 15C | cross power |

EXPERIMENT 16:


| | |
|-------------------------|------------------------------|
| observation | narrow line, low fringe rate |
| simulator | hardware |
| correlation coefficient | 0.5 |
| fringe rate, antenna 1 | 7.8542 Hz |
| fringe rate, antenna 2 | 1000.00 Hz |
| integration length | 54 Msamples |
| figure 16A | station 1 |
| figure 16B | station 2 |
| figure 16C | cross power |

COMMENTS ON LOW FRINGE RATE EXPERIMENTS PERFORMED ON THE SOFTWARE SIMULATOR:

Three runs with the software simulator were used to measure errors in the cross-correlation phase when the baseline fringe rates are very low. In the case of a geocentric coordinate system, however, the individual station lobe rotator rates generally remain high. The simulator runs were for 128 Msamples each. The baseline phase error along with the baseline and station rates are shown below;

| baseline phase error | station fringe rate | baseline fringe rate |
|-----------------------------|---------------------|----------------------|
| -10.98 deg. \pm 0.02 deg. | 2345.84 Hz | 0.17 Hz |
| 0.40 deg. \pm 0.02 deg. | 2345.84 Hz | 0.50 Hz |
| 0.08 deg. \pm 0.02 deg. | 2345.84 Hz | 1.70 Hz |

The large phase error of 11 deg. at 0.17 Hz decreases to 0.4 deg as difference between the fringe rate of the two stations increases to 0.5 Hz. The worst case for low fringe rates will be the Pie Town to VLA baseline at 327 MHz. a detailed model of that baseline has shown that the fringe rate remains between + and - 0.5 Hz. for under 10 minutes. For such a short time interval in the most extreme case we can just flag the low fringe rate recorders at a cost of minimal data loss.



9-1-87 to 9-11-87 CC= 0.5 957 meg 467200 ffts 550_32e '** 774 data **'





FIGURE 2A



9-1-87 to 9-11-87 CC= 0.5 957 meg 467200 ffts 550_32e '** 774 data **'





FIGURE 2B



9-1-87 to 9-11-87 CC= 0.5 957 meg 467200 fite 550_32e '** 774 data **'




FIGURE 2C

9-1-87 to 9-11-87 CC= 0.5 957 meg 467200 ffts 550_32e '** 774 data **'




FIGURE 20

9-1-87 to 9-11-87 CC= 0.5 957 meg 467200 ffts 550_32e '** 774 data **'




FIGURE 2E

9-1-87 to 9-11-87 CC= 0.5 957 meg 467200 ffts 550_32e '** 774 data **'





FIGURE 2F

Continuum, xc = 0.5. 128 Msamples. Two-bit. FAST82.TBL.



Continuum, xc = 0.5. 128 Msamples. Two-bit. FAST82.TBL.





FIGURE 3



9-15-87 to 9-18-87 CC=0.95 200 meg 98400 ffts 550_32e '774 data'





FIGURE 4A



9-15-87 to 9-18-87 CC=0.95 200 meg 98400 fts 550_32e '** 774 data **'





FIGURE 4B



9-15-87 to 9-18-87 CC=0.95 200 mag 98400 f/ta 550_32e '**774 data**'






FIGURE 4C


Narrow line test, xc = 0.5. 128 Msamples. Two-bit. FAST81.TBL.




Narrow line test, xc = 0.5. 128 Msamples. Two-bit. FAST81.TBL.




Narrow line test, $x_c = 0.5$. 128 Msamples. Two-bit. FAST81.TBL.



Narrow line test, $x_c = 0.5$. 128 Msamples. Two-bit. FAST81.TBL.





9-18-87 to 9-24-87 CC=0.5 438 meg 213600 ffts 550_32e '** 774 data **'





FIGURE 6A



9-18-87 to 9-24-87 CC=0.5 438 meg 213600 ffts 550_32e '** 774 data **'





FIGURE 6B

Narrow line test, xc = 0.95. 32 Msamples. Two-bit. FAST85.TBL.



Narrow line test, xc = 0.95. 32 Msamples. Two-bit. FAST85.TBL.





FIGURE 7A

Narrow line test, $x_c = 0.95$. 32 Msamples. Two-bit. FAST85.TBL.



Narrow line test, $x_c = 0.95$. 32 Msamples. Two-bit. FAST85.TBL.





FIGURE 78



10-7-87 to 10-8-87 CC=0.95 103 meg 50400 ffts 550_32e '** 774 data **'





FIGURE 8A



10-7-87 to 10-8-87 CC=0.95 103 meg 50400 ffts 550_32e '87 774 data 87'





FIGURE 8B



10-7-87 to 10-8-87 CC=0.95 103 meg 50400 ffls 550_32e '** 774 data **'





FIGURE 8C

Absorption line test, xc = 0.5. 128 Msamples. Two-bit. FAST68.TBL.



Absorption line test, xc = 0.5. 128 Msamples. Two-bit. FAST68.TBL.





FIGURE 9A

Absorption line test, $x_c = 0.5$. 128 samples. Two-bit. FAST68.TBL.



Absorption line test, $x_c = 0.5$. 128 Msamples. Two-bit. FAST68.TBL.





FIGURE 9B



9-24-87 to 9-28-87 CC=0.7 238 meg 116000 ffs 550_32e '** 774 data **'





FIGURE 10A



9-24-87 to 9-28-87 CC=0.7 238 mag 116000 f/te 550_32e '** 774 data **'





FIGURE 10B



9-24-87 to 9-28-87 CC=0.7 238 meg 116000 ffts 550_32e '** 774 data **'





FIGURE 10C



10-10-87 to 10-12-87 CC=0.95 152 meg 73600 ffts 550_32e '** 774 data **'





FIGURE 11A



10-10-87 to 10-12-87 CC=0.95 152 meg 73600 fts 550_32e '** 774 data **'





FIGURE 118



10-4-87 to 10-7-87 CC=0.5 200 meg 97600 ffts 550_32e '** 774 data **'





FIGURE 12A



10-4-87 to 10-7-87 CC=0.5 200 meg 97600 fflts 550_32a '** 774 data **'





FIGURE 12B



10-4-87 to 10-7-87 CC=0.5 200 meg 97600 ffs 550_32e '** 774 data **'





FIGURE 12C

Narrow line test, xc = 0.5. 128 Msamples. One-bit. FAST80.TBL.



Narrow line test, xc = 0.5. 128 Msamples. One-bit. FAST80.TBL.





FIGURE 13A

Narrow line test, $x_c = 0.5$. 128 samples. One-bit. FAST80.TBL.



Narrow line test, $x_c = 0.5$. 128 Msamples. One-bit. FAST80.TBL.





FIGURE 13B



10-8-87 to 10-10-87 CC=0.5 127 meg 61600 ffts 550_32e '** 774 data **'





FIGURE 14A



10-8-87 to 10-10-87 CC=0.5 127 mag 61600 ffts 550_32e '** 774 data **'





FIGURE 14B



10-8-87 to 10-10-87 CC=0.5 127 meg 61600 ffts 550_32e '** 774 data **'





FIGURE 14C



10-12-87 to 10-13-87 CC=0.5 95 meg 46400 ffts 550_32e '** 774 data **'





FIGURE 15A



10-12-87 to 10-13-87 CC=0.5 95 meg 48400 ffs 550_32e '** 774 data **'





FIGURE 15B



10-12-87 to 10-13-87 CC=0.5 95 meg 46400 ffts 550_32e '** 774 data **'





FIGURE 15C



10-13-87 to 10-14-87 CC=0.5 54 meg 26400 ffts 550_32a '** 774 data **'





FIGURE 16A



10-13-87 to 10-14-87 CC=0.5 54 mag 26400 lfts 550_32e '** 774 data **'





FIGURE 16B



10-13-87 to 10-14-87 CC=0.5 54 meg 26400 ffts 550_32a '** 774 data **'




FIGURE 16C